

I CLAIM

1. Apparatus for processing data, said apparatus comprising:
 - (i) a shifting circuit; and
 - (ii) a bit portion selecting and combining circuit; and
 - 5 (iii) an instruction decoder responsive to an instruction to control said shifting circuit and said bit portion selecting and combining circuit to perform an operation upon a data word R_n and a data word R_m , wherein said operation yields a value given by:
 - (iv) selecting a first portion of bit length A of said data word R_n extending
 - 10 from one end of said data word R_n ;
 - (v) selecting a second portion of bit length B of said data word R_m subject to an arithmetic right shift specified as a shift operand within said instruction; and
 - (vi) combining said first portion and said second portion to form respective different bit position portions of an output data word R_d .
- 15 2. Apparatus as claimed in claim 1, wherein said first portion extends from a most significant bit end of said data word R_n .
3. Apparatus as claimed in claim 1, wherein said first portion extends from a least
- 20 significant bit end of said data word R_n .
4. Apparatus as claimed in claim 1, wherein said shift operand can specify any amount of arithmetic right shift to apply to said data word R_m .
- 25 5. Apparatus as claimed in claim 1, wherein said first portion and said second portion abut within said output data word R_d .
6. Apparatus as claimed in claim 5, wherein said output data word has a bit length of C and $C = A + B$.
- 30 7. Apparatus as claimed in claim 6, wherein $A = B$.

8. Apparatus as claimed in claim 1, wherein $A = 16$.

9. Apparatus as claimed in claim 1, wherein $B = 16$.

5

10. Apparatus as claimed in claim 1, wherein said instruction is a single-instruction-multiple-data instruction.

11. Apparatus as claimed in claim 1, wherein said instruction combines a data value pack operation with a shift operation.

10

12. Apparatus as claimed in claim 1, wherein said shifting circuit is upstream of said selecting and combining circuit in a data path of said apparatus.

13. Apparatus as claimed in claim 12, wherein said selecting and combining circuit is disposed in parallel to an arithmetic circuit within said data path.

15

14. A method of data processing, said method comprising the steps of decoding and executing an instruction that yields a value given by:

(i) selecting a first portion of bit length A of said data word R_n extending from one end of said data word R_n ;

20

(ii) selecting a second portion of bit length B of said data word R_m subject to an arithmetic right shift specified as a shift operand within said instruction; and

(iii) combining said first portion and said second portion to form respective different bit position portions of an output data word R_d .

25

15. A computer program product comprising a computer program for controlling a computer to perform a method as claimed in claim 14.

30